



F004G22A071.A Anodized Black

# Landlord Spot Ø50 PWM Dimmable Anodized

Designed by Piero Lissoni



Spot adjustable head for installation on ground poles or on wall base. Poles and base to be ordered as separated accessories. Heads are equipped with a dismountable ferrule, to insert flood lens or up to two honeycombs, (to be ordered as separate accessories). 24V remote power supply to be ordered separately. Each head comes with a 2000 mm lenght outgoing cable and a wiring kit.

Are you a professional and your project needs consulting and support?

BOOK AN APPOINTMENT

#### Main specifications

Mounting	Wall, Ground	
Environments	Outdoor wet location	
LED type	Power LED	
Lamp category	LED	
Ilcos	No	
Power (W)	7.2	
System flux (lm)	442	

#### Physical

Colour	Anodized Black	
Trim	No	
Orientation	Adjustable	
Rotation (°)	359	
Transversal tilting (°)	120	
Net weight (kg)	0.35	
IP internal	66	



Mounting instructions

₹ ZIP

Photometric Files

LDT / IES

₹ ZIP

**Technical Drawings** 

2D	<u>↓</u> ZIP
3D	<b>⊥</b> ZIP
<b>⋒</b> Bim	.↓. ZIP











https://professional.flos.com/en/global/product/landlord-spot-50-pwm-dimmable-anodized-black-f004g22a071.a/

F004G22A071.A

#### Schematic light drawing



Beam Angle:		26
h(m)	E(lx)	D(n
1	1875	0.4
2	469	0.9
3	208	1.4
4	117	1.8
5	75	23

beam Angle.		20
h(m)	E(lx)	D(n
1	1875	0.4
2	469	0.9
3	208	1.4
4	117	1.8

### **Ecodesign and Energy** Labelling

This product contains a light source of energy efficiency class E



Replaceable (LED only) light source by a professional

#### Photometric

Lighting type	Direct
Light distribution	Symmetric
CCT (K)	2700
CRI>	80
Beam angle C0-180 (°)	24
Beam angle C90-270 (°)	24

#### Electrical

Insulation class	III
Frequency (Hz)	50-60
Main voltage (Vac)	24
Driver	Remote excluded
Dimmable	Yes
Dimming type  Non Dimmable, Dimmable 1-10 Dimmable DALI PWM	
Emergency type	No

#### **Notes**

Carefully install and maintain the fixtures to avoid damaging the coating. For LED fixtures, most problems are tied to electrical issues related to the insulation, which may cause destructive electrical discharges.

These are frequently caused by:

- power surges from the power network where fixture is connected.
- electrostatic discharge (ESD) from the environment.

We recommend installing a power-surge protection device on the fixture to reduce the intensity of these effects and prevent irreversible damages. The specific device should be chosen based on the electrical characteristics.

#### **Accessories & Power Supply**



REQUIRED Power supply

RF25754

'Power supply dual function Vout 24Vdc: 8W/100÷240V lout 350ma: 6x1W/100÷240V IP20 Class II selv.\_Non Dimmable



### REQUIRED Power supply

RF25757

Power supply 24V 10W / 110-240V IP67 Class II selv.\_Non Dimmable



#### REQUIRED Accessory

F004Z0A007

Wall base Anodized Black



#### REQUIRED Accessory

F004Z0F007

Pole with base H 900 mm Anodized Black



#### REQUIRED Accessory

F004Z0E0071

Pole with base H 600 mm Anodized Black



#### REQUIRED Accessory

F00470D007

Pole with base H 300 mm Anodized Black



### REQUIRED Power supply

RF25747

Power supply 24V 10W /110-240V IP20 Class II selv. Non Dimmable



### REQUIRED Power supply

RF25748

Power supply dual function Vout 24Vdc: 8W/100÷240V lout 350ma: 6x1W/100÷240V IP65 Class II selv. Non Dimmable



#### REQUIRED Power supply

EGGNRANA

CONTROL INTERFACE 24V PWM -1..10V IP67 CLASS III. VIN 24Vdc 120W (POWER SUPPLY NOT INCLUDED)



#### REQUIRED Power supply

F990B04A000

POWER SUPPLY 24V PWM WITH 1..10V CONTROL INTERFACE IP67 CLASS II. Vin 120-270Vac 70W



### REQUIRED Power supply

F990R02A000

POWER SUPPLY 24V PWM WITH 1..10V CONTROL INTERFACE IP67 CLASS II. Vin 120-270Vac 35W



### REQUIRED Power supply

F990B03A000

POWER SUPPLY 24V PWM WITH DALI CONTROL INTERFACE IP67 CLASS II. Vin 120-270Vac 35W



#### REQUIRED Power supply

F990B01A000

CONTROL INTERFACE 24V PWM -DALI IP67 CLASS III. Vin 24Vdc 120W (POWER SUPPLY NOT INCLUDED)



## REQUIRED Power supply

F990R05A000

POWER SUPPLY 24V PWM WITH DALI CONTROL INTERFACE IP67 CLASS II. Vin 120-270Vac 70W



#### REQUIRED Power supply

F990R23A700

Power supply 24Vdc 35W /120-270V IP67 Class II selv.



### REQUIRED Power supply

E990R16A00

POWER SUPPLY 24V PWM WITH PUSH CONTROL INTERFACE IP67 CLASS II. Vin 120-270Vac 35W



REQUIRED Power supply

F990B17A000

POWER SUPPLY 24V PWM WITH PUSH CONTROL INTERFACE IP67 CLASS II. Vin 120-270Vac 70W



REQUIRED Power supply

F990B27A000

Power supply 24Vdc 70W / 220-240V IP67 Class I selv. Non Dimmable



#### REQUIRED Power supply

F990R28A000

Power supply 24Vdc 50W / 220-240V IP67 Class I selv. Non Dimmable



#### OPTIONAL Accessory

F990C00A000

2 way terminal block 4 poles IP68 H20 stop. (ø5,5÷12mm cable)



#### OPTIONAL Accessory

F990C010000

3/4 way terminal block 4 poles IP68 H2O stop. (ø5,5÷12mm cable)



#### OPTIONAL Accessory

F004Z0L0000

Honeycomb



#### OPTIONAL Accessory

004Z0H0000

Flood lens



#### OPTIONAL Accessory

F004Z070000

Tree strap



OPTIONAL Accessory

F004Z060000

Earth stick